

## VARIABLE ATTENUATOR

# FVA-3100

R&D AND MANUFACTURING – OPTICAL



- Singlemode and multimode
- Monitor output option
- Ultra-low insertion loss
- Programmable—using the front-panel buttons, or the built-in RS-232 or GPIB interfaces



[www.EXFO.com](http://www.EXFO.com)  
Telecom Test and Measurement

**EXFO**  
EXPERTISE REACHING OUT

## First-Class Building Block for Assessing Signal Attenuation

High-quality components and meticulous calibration procedures make the FVA-3100 Variable Attenuator the instrument of choice for repeatable and accurate attenuation settings (up to 100 dB). The FVA-3100 meets system and component manufacturers' need for component and system loss simulation, instrument calibration, power meter linearity measurement and spectral tuning. Its ultra-low insertion loss enables you to optimize the loss budget.

The FVA-3100 is configured for singlemode or multimode fibers. Use it as a stand-alone instrument or mounted on a 19-inch rack (optional).



FVA-3100 with monitor port.

### APPLICATIONS

- BER testing
- EDFA characterization
- System/component loss simulation
- Accurate power-level monitoring
- Instrument calibration
- Linearity measurement
- Precision variable optical source output
- Spectral tuning
- Optical margin analysis

### KEY FEATURES

#### — Attenuation modes

Choose from three attenuation modes: absolute (including insertion loss), relative (in reference to the 0.00 dB level) or X+B (relative display to any selected reference value).

#### — Monitor port

The monitor output port enables accurate power-level monitoring at the receiver end of your system.

### PROGRAMMABLE AND REMOTELY CONTROLLABLE

Using the front-panel buttons, cycle through a repeatable sequence of up to 100 attenuation steps, with a dwell time of up to 1000 hours per step. The Program mode is ideal for automated bit-error-rate (BER) testing and linearity measurements.

The FVA-3100 can also be programmed remotely through its RS-232 or GPIB interfaces.

### EASY TO USE

Access most functions at the touch of a button and manually change attenuation with the FVA-3100's user-defined steps or on-display value editing. The standard GPIB and RS-232 interface and control codes enable remote operation from a PC or test station. Program your own software solutions for complex test procedures and benefit from added computer capabilities. LabVIEW® drivers are available.

## SPECIFICATIONS <sup>a</sup>

### SINGLEMODE CONFIGURATIONS

| Description                           | SMF without monitor port | SMF with monitor port |
|---------------------------------------|--------------------------|-----------------------|
| <b>Models</b>                         | <b>FVA-3100-B</b>        | <b>FVA-3100-BM</b>    |
| Fiber type (μm)                       | 9/125                    | 9/125                 |
| Wavelength range (nm)                 | 1200 to 1650             | 1200 to 1650          |
| Max. attenuation (dB)                 | ≥ 70                     | ≥ 70                  |
| Insertion loss <sup>b, c</sup> (dB)   | Typical                  | 1.1                   |
|                                       | Max.                     | 1.8                   |
| Resolution (dB)                       | 0.005                    | 0.005                 |
| Linearity <sup>d</sup> (dB)           | ± 0.1                    | ± 0.1                 |
| Repeatability (dB)                    | ± 0.03                   | ± 0.03                |
| Max. PDL <sup>e</sup> (dB)            | 0.2                      | 0.2                   |
| Typ. return loss <sup>b, f</sup> (dB) | > 55                     | > 55                  |
| Max. input power <sup>g</sup> (dBm)   | 20                       | 20                    |
| Shutter isolation (dB)                | > 100                    | > 100                 |
| Typ. monitor output (dB)              | -                        | 14.5                  |

### MULTIMODE CONFIGURATIONS

| Description                           | MMF without monitor port  | MMF with monitor port  |
|---------------------------------------|---------------------------|------------------------|
| <b>Models</b>                         | <b>FVA-3100-C, D, E</b>   | <b>FVA-3100-CM, DM</b> |
| Fiber type (μm)                       | 50/125, 62.5/125, 100/140 | 50/125, 62.5/125       |
| Wavelength range (nm)                 | 700 to 1350               | 700 to 1350            |
| Max. attenuation (dB)                 | ≥ 65                      | ≥ 65                   |
| Insertion loss <sup>b, c</sup> (dB)   | Typical                   | 1.3                    |
|                                       | Max.                      | 2.0                    |
| Resolution (dB)                       | 0.01                      | 0.01                   |
| Linearity <sup>d</sup> (dB)           | ± 0.1                     | ± 0.1                  |
| Repeatability (dB)                    | ± 0.03                    | ± 0.03                 |
| Typ. return loss <sup>b, f</sup> (dB) | > 25                      | > 25                   |
| Max. input power <sup>g</sup> (dBm)   | 20                        | 20                     |
| Shutter isolation (dB)                | > 100                     | > 100                  |
| Typ. monitor output (dB)              | -                         | 14.5                   |

#### Notes

- At 23 °C ± 5 °C.
- Measured at 1310 nm and 1550 nm for singlemode units, measured at 850 nm and 1300 nm for multimode units.
- Measured with FC/UPC connectors for singlemode units and FC/PC for multimode units.
- Measured at 1310 nm and 1550 nm (up to 60 dB) for singlemode units and 850 nm and 1300 nm (up to 50 dB) for multimode units, non-polarized light.
- Measured at 1550 nm, attenuation of < 30 dB.
- The return loss is limited by the return loss of the connectors. The connectors used are FC/APC for singlemode units and FC/PC for multimode units.
- Typical value. Prolonged exposure may damage the unit.

## GENERAL SPECIFICATIONS

|                   |                            |                                       |
|-------------------|----------------------------|---------------------------------------|
| Size (H X W X D)  | 117 mm X 222 mm X 333 mm   | (4 5/8 in X 8 3/4 in X 13 1/8 in)     |
| Weight            | 2.6 kg                     | (5.8 lb)                              |
| Temperature       | Operating                  | 0 °C to 40 °C<br>(32 °F to 122 °F)    |
|                   | Storage                    | -40 °C to 70 °C<br>(-40 °F to 158 °F) |
| Relative humidity | 0 % to 80 % non-condensing |                                       |

### Instrument Drivers

LabVIEW™ drivers and SCPI commands.

### Remote Control

GPIO (IEEE-488.1, IEEE-488.2), RS-232.

### Standard Accessories

User guide, Certificate of Compliance, Certificate of Calibration and AC power cord.

## ORDERING INFORMATION

### FVA-3100-X-XX

#### Model

FVA-3100-B = 9/125 µm  
 FVA-3100-C = 50/125 µm  
 FVA-3100-D = 62.5/125 µm  
 FVA-3100-E = 100/140 µm  
 FVA-3100-BM = 9/125 µm with monitor output  
 FVA-3100-CM = 50/125 µm with monitor output  
 FVA-3100-DM = 62.5/125 µm with monitor output

Example: FVA-3100-BM-EI-EUI-89

#### Note

a. Only available for singlemode models.

#### Connector

EI-EUI-28 = UPC/DIN 47256  
 EI-EUI-76 = UPC/HMS-10/AG  
 EI-EUI-89 = UPC/FC narrow key  
 EI-EUI-90 = UPC/ST  
 EI-EUI-91 = UPC/SC  
 EI-EUI-95 = UPC/E-2000  
 EA-EUI-28 = APC/DIN 47256 <sup>a</sup>  
 EA-EUI-89 = APC/FC narrow key <sup>a</sup>  
 EA-EUI-91 = APC/SC <sup>a</sup>  
 EA-EUI-95 = APC/E-2000 <sup>a</sup>



**Rugged Handheld Solutions**

|                 |                                      |
|-----------------|--------------------------------------|
| <b>OPTICAL</b>  | <b>COPPER ACCESS</b>                 |
| - OTDRs         | - ADSL/ADSL2+, SHDSL, VDSL test sets |
| - OLTs          | - VoIP and IPTV test sets            |
| - Power meters  | - Ethernet test sets                 |
| - Light sources | - POTS test sets                     |
| - Talk sets     |                                      |



**Platform-Based Solutions**

|                        |                                 |  |
|------------------------|---------------------------------|--|
| <b>OPTICAL FIBER</b>   | <b>DWDM TEST SYSTEMS</b>        | <b>TRANSPORT AND DATAKOM</b>                 |
| - OTDRs                | - OSAs                          | - Next-generation SONET/SDH and OTN testers  |
| - OLTs                 | - PMD analyzers                 | - SONET/DSn (DS0 to OC-192) testers          |
| - ORL meters           | - Chromatic dispersion analyzer | - SDH/PDH (64 kbit/s to STM-64) testers      |
| - Variable attenuators |                                 | - T1/T3, E1 testers                          |
|                        |                                 | - 10/100 Mbit/s and Gigabit Ethernet testers |
|                        |                                 | - Fibre Channel testers                      |
|                        |                                 | - 10 Gigabit Ethernet testers                |

Find out more about EXFO's extensive line of high-performance portable instruments by visiting our website at [www.EXFO.com](http://www.EXFO.com).

EXFO Corporate Headquarters > 400 Godin Avenue, Quebec City (Quebec) G1M 2K2 CANADA | Tel.: 1 418 683-0211 | Fax: 1 418 683-2170 | [info@EXFO.com](mailto:info@EXFO.com)

Toll-free: 1 800 663-3936 (USA and Canada) | [www.EXFO.com](http://www.EXFO.com)

|                     |   |                           |                          |
|---------------------|---|---------------------------|--------------------------|
| <b>EXFO America</b> | 3701 Plano Parkway, Suite 160<br>Plano, TX 75075 USA  | Tel.: 1 800 663-3936      | Fax: 1 972 836-0164      |
| <b>EXFO Europe</b>  | Omega Enterprise Park, Electron Way<br>Chandlers Ford, Hampshire S053 4SE ENGLAND                                       | Tel.: +44 2380 246810     | Fax: +44 2380 246801     |
| <b>EXFO Asia</b>    | 151 Chin Swee Road, #03-29 Manhattan House<br>SINGAPORE 169876  | Tel.: +65 6333 8241       | Fax: +65 6333 8242       |
| <b>EXFO China</b>   | No.88 Fuhua, First Road<br>Central Tower, Room 801, Futian District<br>Shenzhen 518048, CHINA                           | Tel.: +86 (755) 8203 2300 | Fax: +86 (755) 8203 2306 |
|                     | Beijing New Century Hotel Office Tower, Room 1754-1755<br>No. 6 Southern Capital Gym Road<br>Beijing 100044 P. R. CHINA | Tel.: +86 (10) 6849 2738  | Fax: +86 (10) 6849 2662  |

EXFO is certified ISO 9001 and attests to the quality of these products. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. All of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit [www.EXFO.com/recycle](http://www.EXFO.com/recycle). However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.

For the most recent version of this spec sheet, please go to the EXFO website at <http://www.EXFO.com/specs>

In case of discrepancy, the Web version takes precedence over any printed literature.