



*A cost effective alternative for analog cellular, SSB, paging and mobile radio testing*

- Analog meter and VFD (Vacuum Fluorescent Display) offer high visibility in all lighting conditions
- Convenient service analyzer with duplex and simplex connectors
- Standard internal spectrum analyzer to 1 GHz
- Built-in 1 MHz oscilloscope
- Comprehensive testing of analog and advanced digital paging with the AC510 option

#### RF Solutions

Designed for land mobile professionals with demanding RF testing requirements, the 1200 Super S has a sensitive 2  $\mu$ V triple conversion receiver capable of monitoring AM, FM and SSB carriers within the low band, VHF, UHF and high band ranges.

Depending on your specific needs, the 1200 Super S also gives you the choice of receiving straight "off the air" or through a direct connection to a T/R port.

Recognized for its versatility, the 1200 Super S supports DCS, DTMF and pulsed audio signaling formats.

The 1200 Super S also meets RF measurement needs for:

- RF frequency error
- RF power
- Audio frequency error
- CTCSS frequency
- CTCSS modulation

In duplex mode the 1200 Super S is capable of simultaneously generating and

## 1200 Super S Communications Service Monitor



receiving frequency offsets in 2.5 kHz steps. The duplex feature can be configured to operate in three modes:

- Testing using separate transmit and receive ports
- Testing using one common transmit/receive port
- "Off-the-air" duplex testing

With standard features like a 1000 MHz spectrum analyzer and built-in 1 MHz oscilloscope, the 1200 Super S virtually eliminates the need for costly additional equipment purchases. An optional tracking generator makes cable testing simple.

#### Paging Solutions

The versatility of the 1200 Super S also allows comprehensive testing of the most popular paging protocols, including encode/decode or 2-tone sequential, 5/6 Tone testing..

For those involved with advanced paging protocol systems, the AC510 option supports the following paging standards:

- Flex
- POCSAG
- Golay Sequential Code (GSC)
- NEC D3

#### Trunking Solutions

With the CLEARCHANNEL LTR<sup>®</sup> trunking option, the 1200 Super S is an ideal platform for testing LTR mobiles, portables and repeaters. For basic repeater testing, the 1200 Super S allows you to perform extensive receiver and transmitter tests. For more in-depth analysis, the LTR test option emulates the repeater system and

allows testing of home repeater access and next repeater access, including Handshake and Hand-off operation.

In addition, with 760 trunking channels, an internal LTR tracking generator and user friendly LTR programming screens, the 1200 Super S is designed to give you the greatest control and flexibility possible.

#### Complex Functionality That's Simple to Use

From the user interface to functions and displays, the 1200 Super S allows technicians of any skill level to fully utilize its vast testing resources.

- Intuitive user interface makes complex testing simple and efficient.
- CTCSS encode/decode feature makes it easy to work with sub-audible tones.
- A standard RS-232 port allows remote testing.
- Internal memory allows storage of up to 99 RF frequencies.

From programming automatic test sequences to executing standard measurements, the operating system of the 1200 Super S provides a high level of testing. Yet the 1200 Super S is so user-friendly, you'll spend less time setting up tests and more time testing.

# 1200 Super S

## Specification

### RF Signal Generator

**Frequency Range**  
250 kHz to 999.9999 MHz

**Resolution**  
100 Hz

**Accuracy**  
Same as Master Oscillator

### Output (T/R)

**Range**  
-127 to -20 dBm

**Resolution**  
10 dB steps with 11 dB vernier

**Accuracy**  
2.5 dB  
3.0 dB @ -20 dB attenuator setting

**Spectral Purity Harmonics**  
-30 dBc

**Spectral Purity Nonharmonics**  
-55 dBc

**IF Image**  
≤ -35 dB

**Residual FM**  
< 100 Hz (RMS, 0.3 to 3 kHz BW)

**Input Protection**  
150 W

### Duplex Generator

**Frequency Range**  
0 to ±49.9975 MHz from receive frequency

**Resolution**  
2.5 kHz

**Accuracy**  
See Master Oscillator

**Duplex Output Level**  
-40 dBm (Low), -15 dBm (High) into 50 Ω

**Input Protection**  
0.25 W

**T/R Port**  
-85 dBm ±10 dB fixed level

### Modulation

**Internal Frequency Modulation Range**  
0 to 50 kHz (1 kHz tone)

**FM Rate**  
10 Hz to 30 kHz (Internal)  
2 Hz to 30 kHz (External) (DC when in variable generate)

**FM Accuracy**  
±5% of reading, ±3% of full scale (1 kHz tone)

**FM Distortion**  
< 1% (to 20 kHz deviation)

**EXT MOD Sensitivity**  
0.1 VRMS/kHz (-0% + 30%)

**Amplitude Modulation Range**  
0 to 90%

**AM Rate**  
10 Hz to 10 kHz (30% maximum modulation above 5 kHz)

**AM Accuracy**  
±5% of reading, ±3% of full scale (1 kHz tone)

**AM Distortion**  
< 10% (to 60% modulation)

**EXT MOD sensitivity**  
0.01 VRMS (0% to +30%)

### Audio Generators

**Generator #1 Frequency Range**  
1 kHz

**#1 Accuracy**  
Same as Master Oscillator

**#1 Output Range**  
0 to 2.5 V (RMS, into 150 Ω)

**#1 Distortion**  
< 0.5%

**#1 Waveshape**  
Sine

**Audio Generator #2 Frequency Range:**  
10 Hz to 30 kHz

**#2 Resolution**  
0.1 Hz

**#2 Accuracy**  
±0.01%

**#2 Output Range**  
0 to 2.5 V (RMS, into 150 Ω)

**#2 Distortion (at 2.5 VRMS)**  
< 2% (10 Hz to 100 Hz) < 0.7% (100 Hz to 30 kHz)

**#2 Waveshapes**  
Sine, Square, Ramp, Triangle, TTL

### Receiver

**Frequency Range**  
100 kHz to 999.9999 MHz

**Resolution**  
100 Hz

**Sensitivity**  
2 μV typical (1 MHz to 1000 MHz, FM narrow)

**Antenna Input Protection**  
0.25 W

### Selectivity

Mode	Rx BW	AF BW
FM WIDE	200 kHz	80 kHz
FM MID	200 kHz	8 kHz
FM NAR	15 kHz	8 kHz
SSB	6 kHz	8 kHz
AM NAR	6 kHz	8 kHz
AM NORM	15 kHz	8 kHz

### Adjacent Channel Rejection

Rx BW	BW > 40 dB Down
200 kHz	±300 kHz
15 kHz	±27 kHz
6 kHz	±12 kHz

### Demodulation Output

**AM Output Level**  
5 mV RMS/%

**FM Output Level**  
60 mV RMS/1 kHz

**Impedance**  
600 Ω

### RF Frequency Error Meter

**Meter Range**  
± 30 Hz to ± 10 kHz (full scale, 1-3-10 sequence)

**Meter Accuracy**  
± Master Oscillator, +3% of full scale

### AF Frequency Error Meter

**Frequency Range**  
10 Hz to 12 kHz

**Meter Range**  
±3 Hz to ±300 Hz (full scale, decade sequence)

**Meter Accuracy**  
±0.01%, ±3% of full scale

### FM Deviation Meter

**Meter Range**  
2 kHz to 60 kHz (full scale, 2-6-20 sequence)

**Meter Accuracy**  
±5% of reading, ±3% of full scale (1 kHz tone)

### AM Modulation Meter

**Meter Range**  
60% and 200% full scale

**Meter Accuracy**  
±5% of reading, ±3% of full scale (1 kHz tone)

### RF Power Meter

**Input Level Ranges**  
0 to 15 W and 0 to 150 W (peak or average responding)

**Accuracy**  
±7% of reading, ±3% of full scale (1 to 600 MHz)  
±20% of reading, ±3% of full scale (600 to 1000 MHz)

**Operating Conditions**  
50 W continuous  
>50 W to 150 W (1 min ON, 5 min OFF)

### Distortion Meter

**Range**  
0 to 20% at 1 kHz

**Accuracy**  
± 1% (at 10% distortion)

**Signal Frequency**  
1 kHz

**Input Level**  
0.25 to 2 VRMS

**Input Impedance**  
10 kΩ nominal

### SINAD Meter

**Range**  
3 to 20 dB at 1 kHz

**Accuracy**  
± 1 dB (at 12 dB SINAD)

**Signal Frequency**  
1 kHz

**Input Level**  
0.25 to 2 VRMS

**Input Impedance**  
10 kΩ nominal

### Spectrum Analyzer

**Level Display**  
10 dB/div

**Dynamic Range**  
70 dB

**Log Linearity**  
±2 dB (-90 to -30 dBm)

### Frequency Span Modes

Scan Width	RBW
1 MHz/div	30 kHz
500 kHz/div	30 kHz
200 kHz/div	30 kHz
100 kHz/div	30 kHz
50 kHz/div	30 kHz
20 kHz/div	3 kHz
10 kHz/div	3 kHz
5 kHz/div	3 kHz
2 kHz/div	300 Hz
1 kHz/div	300 Hz

### Oscilloscope

**Bandwidth (3 dB)**  
DC to 1 MHz

**Input Ranges**  
10 mV/div to 10 V/div (decade sequence)

**Horizontal Sweep Rate**  
10 msec/div to 10 μsec/div (decade sequence)

## Digital Voltmeter

### AC VOLTS

**Voltage Range**  
0 to 100 VRMS

**Accuracy**  
10% ± 2 counts

**Frequency Range**  
45 Hz to 10 kHz

### DC VOLTS

**Voltage Range**  
0 to 100 V

**Accuracy**  
10% ± 2 counts

## Master Oscillator

### TCXO

**Temperature Stability**  
±0.2 ppm (0 to 50°C)

**Ageing**  
±0.5 ppm/year

## Power Requirements

**Line Voltage**  
105 to 130 VAC  
210 to 260 VAC

**Frequency**  
50 to 400 Hz

**Power Consumption**  
60 W typical

**DC Input**  
12 to 30 VDC

## General Characteristics

**Dimensions**  
332 mm (13.06 in) wide, 185 mm (7.3 in) high,  
445 mm (17.5 in) deep

**Weight**  
17.2 kg (38 lbs) without options

## 0.05 ppm OCXO (Premium)

**Stability**  
0.05 ppm/year (0 to 50°C)

## Generate Amplifier (Premium)

**Gain**  
30 dB (±2 dB) typical, 250 kHz to 1000 kHz

**Test Set Output with Analyzer Installed**  
Variable to +10 dBm, FM and CW  
Variable to +4 dBm, AM

## Tracking Generator (Premium)

**Frequency Range**  
1 to 999.9999 MHz

**Output Level**

Track High	-5 dBm (+3/-5 dB)
Track Mid	-15 dBm (±7 dB)
Track Low	-40 dBm (+5/-10 dB)

**Flatness**  
±1 dB over center 30% of display  
±5 dB over remaining display

**Tracking Span**  
10 kHz to 10 MHz

**Output Impedance**  
50 Ω (nominal)

### Spurious

Harmonic and non harmonic are <5 dBc, <10 dB typical  
Image (RF + 180 MHz) 0 dB typical

### Dynamic Range

70 dB

### Tracking Range

200 Hz to 1.0 kHz

## Versions and Accessories

When ordering please quote the full order number information

### Ordering

Numbers	Versions
1200SS-110	1200 Super S, 110 VAC
1200SS-110-C	1200 Super S, 110 VAC with Certificate of Calibration
1200SS-220	1200 Super S, 220 VAC operation
1200SS-220-C	1200 Super S, 220 VAC with Certificate of Calibration
1200SSH-110	1200 Super S Hi Stability (0.05 ppm OCXO time base, tracking generator) 110 VAC operation
1200SSH-110-C	1200 Super S Hi Stability, 110 VAC, Cert. Cal
1200SSH-220	1200 Super S Hi Stability, 220 VAC operation
1200SSH-220-C	1200 Super S Hi Stability, 220 VAC with Certificate of Calibration
<b>Accessories</b>	
AC0002	Soft padded carrying case
AC0488	IEEE-488 (in lieu of RS-232) (not avail. with 1200SSP or AC0450)
AC0489	CLEAR CHANNEL LTR
AC510	Paging encoder
AC1201	Telescopic antenna
AC1205	Microphone
AC2200	Maintenance manual
AC2201	Rack mounting kit
AC4101	Return loss bridge 5 MHz to 1 GHz (req. 1200 Super S Premium)
AC5249	Generate Amplifier +30 dBm

# 1200 Super S



IFR Americas, Inc., 10200 West York Street, Wichita, Kansas  
67215-8999, USA. E-mail: [info@ifrsys.com](mailto:info@ifrsys.com)  
Tel: +1 316 522 4981 Toll Free USA: 1 800 835 2352 Fax: +1 316 522 1360

IFR Ltd, Longacres House, Norton Green Road, Stevenage, Herts  
SG1 2BA, United Kingdom. E-mail: [info@ifrinternational.co.uk](mailto:info@ifrinternational.co.uk)  
Tel: +44 (0) 1438 742200 Freephone UK: 0800 282 388 Fax: +44 (0) 1438 727601

As we are always seeking to improve our products, the information in this document gives only a general indication of the product capacity, performance and suitability, none of which shall form part of any contract. We reserve the right to make design changes without notice. All trademarks are acknowledged. Parent Company IFR Systems, Inc. © IFR Ltd. 1999.

