

PART NUMBER	PROBE DESCRIPTION	INSTRUMENT COMPATIBILITY	RANGE	BANDWIDTH (kHz)	APERTURE SIZE	ACCURACY		
8800 PowerScope/3030, 3060, 3030A PowerProfiler/100G, 100S Powervisa			$\frac{D}{\sqrt{t}}$ RATED			8800 PowerScope	3030A PowerProfiler	100G Powervisa
A-115	60 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	3-60 A_{rms}	1 kHz	0.5" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.03\%$ of full scale $\pm 0.1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-115A	60 Amp Clamp-on SmartProbe (phase correction)	8800, 3030, 3060, 3030A, 100G, 100S	3-60 A_{rms}	3 kHz	0.5" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.01\%$ of full scale $\pm 0.1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-116	600 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	30-600 A_{rms}	3 kHz	2.0" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.01\%$ of full scale $\pm 0.1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-120	3000 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A	150-3000 A_{rms}	3 kHz	2.5" x 6.3" rectangular	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.01\%$ of full scale $\pm 0.1\%$ of reading	
A-121	20 Amp Current Transformer Interface SmartProbe (CTIP)	8800, 3030, 3060, 3030A, 100G, 100S	1-20 A_{rms}	3 kHz	0.375" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.2\%$ of full scale $\pm 0.2\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-705	5 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	0.05-5 A_{rms}	3 kHz	0.5" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.1\%$ of full scale $\pm 0.5\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-705T	5 Amp Current Transformer Interface SmartProbe (CTIP)	8800, 3030, 3060, 3030A, 100G, 100S	0.05-5 A_{rms}	3 kHz	0.375" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.1\%$ of full scale $\pm 0.3\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-713	1000 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	50-1000 A_{rms}	3 kHz	2.0" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.01\%$ of full scale $\pm 0.1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-721	20 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	0.05-20 A_{rms}	3 kHz	0.5" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.05\%$ of full scale $\pm 0.3\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
A-732	300 Amp Clamp-on SmartProbe	8800, 3030, 3060, 3030A, 100G, 100S	15-300 A_{rms}	3 kHz	2.0" round	$\pm 0.3\%$ of full scale $\pm 1.0\%$ of reading	$\pm 0.02\%$ of full scale $\pm 0.1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 0.5\%$ of reading
7100, 8020, 9020 PQNode						7100 PQNode	8020 PQNode	9020 PQNode
CT-5	5 Amp Clamp-on CT Probe	7100, 8020, 9020	0.5-5 A_{rms}	3 kHz	0.5" round	$\pm 2\%$ of full scale $\pm 6\%$ of reading	$\pm 2\%$ of full scale $\pm 6\%$ of reading	$\pm 2\%$ of full scale $\pm 6\%$ of reading
WCT-5	5 Amp Fixed Toroid CT Probe	7100, 8020, 9020	.25-5 A_{rms}	3 kHz	0.375" round	0.1% of full scale 1% of reading	0.1% of full scale 2% of reading	0.1% of full scale 2% of reading
CT-150	150 Amp Clamp-on CT Probe	7100, 8020, 9020	5-150 A_{rms}	3 kHz	cable: 1.18" max busbar: 2" x .25" max	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading
CT-600	600 Amp Clamp-on CT Probe	7100, 8020, 9020	30-600 A_{rms}	3 kHz	2" round	$\pm 1\%$ of full scale $\pm 1\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading
CT-3000	3000 Amp Clamp-on CT Probe	7100, 8020, 9020	150-3000 A_{rms}	3 kHz	2.5" x 6.3" rectangular	$\pm 0.1\%$ of full scale $\pm 1\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading	$\pm 0.2\%$ of full scale $\pm 1.5\%$ of reading
8010, 9010 PQNode						8010 PQNode	9010 PQNode	
A-7251S	250 Amp/500 Amp/1000 Amp Switchable Clamp-on Current Probe	8010, 9010	1-250 A_{rms} 1-500 A_{rms} 1-1000 A_{rms}	10 kHz	2.17" round	$\pm 0.04\%$ of full scale $\pm 0.2\%$ of reading	$\pm 0.04\%$ of full scale $\pm 0.2\%$ of reading	
155 Harmonics Meter/355 Harmonics Analyzer						355 Harmonics Analyzer	155 Harmonics Meter	
A-150	60 Amp RMS Current Probe	355, 155	3-60 A_{rms}	3 kHz	.5" round	$\pm 1\%$ of full scale $\pm 2\%$ of reading	$\pm 1\%$ of full scale $\pm 2.5\%$ of reading	
A-1000	600 Amp RMS Current Probe	355, 155	50-1000 A_{rms}	3 kHz	2" round	$\pm 1\%$ of full scale $\pm 1\%$ of reading	$\pm 1\%$ of full scale $\pm 1\%$ of reading	
A-3000	3000 Amp RMS Current Probe	355, 155	150-3000 A_{rms}	3 kHz	2.5" x 6.3" rectangular	$\pm 0.5\%$ of full scale $\pm 1\%$ of reading	$\pm 0.5\%$ of full scale $\pm 1\%$ of reading	
130 PQSentry						130 PQSentry		
P-130	150 Amp Clamp-on Current Probe	130	1-150 A_{rms}	3 kHz	0.5" round	$\pm 1\%$ of full scale $\pm 5\%$ of reading		