

FG-7005C, FG-7002C, FG-8002



FG-7005C

FG-7005C FEATURES

- 0.02Hz ~ 5MHz Frequency output in 7 Range
- 4-in-1 Sweep, Function & Pulse Generator and Frequency Counter
- Versatile waveforms for Sine, Triangle, Ramp, Pulse Sawtooth and DC outputs
- Built in 6 digit internal and external counter display(Max.50MHz)
- Internal and external linear sweep control from 1:1 to 100:1
- Low distortion for sine waveform less than 1% at 0.2Hz ~ 100kHz
- Variable symmetry for generating sawtooth and pulse waveforms
- TTL and CMOS leveled square waveform output
- Variable DC offset control
- Variable output level control with 20dB attenuator and amplitude control



FG-7002C

FG-7002C FEATURES

- 0.02Hz ~ 2MHz Frequency output in 7 Range
- 4-in-1 Sweep, Function & Pulse Generator and Frequency Counter
- Versatile waveforms for Sine, Triangle, Ramp, Pulse Sawtooth and DC outputs
- Built in 6 digit internal and external counter display(Max.50MHz)
- Internal and external linear sweep control from 1:1 to 100:1
- Low distortion for sine waveform less than 1% at 0.2Hz ~ 100kHz
- Variable symmetry for generating sawtooth and pulse waveforms
- TTL and CMOS leveled square waveform output
- Variable DC offset control
- Variable output level control with 20dB attenuator and amplitude control



FG-8002

FG-8002 FEATURES

- Wide frequency range : 0.02Hz to 2MHz.
- Versatile waveforms : Sine, Triangle, Square, Ramp and Pulse, Sawtooth.
- Low distortion factor less than 1% at 10Hz to 100kHz.
- TTL Leveled square wave output.
- Linear sweep control from 1 : 1 to 100 : 1.
- Variable symmetry to generate sawtooth and pulse waveforms.
- DC offset control.
- Maximum attenuation of 20dB can be obtained.

Specifications

| SPEC | | MODEL | FG-7005C | FG-7002C | FG-8002 |
|---------------------------------|----------------------------|---------------------------------------------------------|---------------------------------------|-----------------|---------------------------|
| FREQUENCY | Output Waveform | Sine, Triangle, Square,Pulse, Sawtooth, Ramp, TTL, CMOS | | | |
| | Frequency Range | 0.05Hz-5MHz in the 7 Ranges | 0.02Hz-2MHz in the 7 Ranges | | |
| | Frequency Accuracy | ±1count | | | ±8% of Full Scale to 2MHz |
| EXTERNAL FREQUENCY CONTROL(VCF) | Input Voltage | 0 to 10V(DC+AC peak) | | | |
| | Frequency Variable Range | 100:1 or More | | | |
| | DC Offset | ±10V(Without Load), ±5V(With Load) | | | |
| | Symmetrical Variable Range | 10:1 to 1:10 or More | | | |
| SINE WAVE | Distortion | Less than 1%(0.2Hz ~ 100kHz) | | | |
| SQUARE WAVE | Rise/Fall Time | Less than 25ns | Less than 110ns | Less than 100ns | |
| TRIANGLE WAVE | Linearity | Less than 1% to 100kHz, Less than 5% to 2MHz | | | |
| TTL OUTPUT | Output | TTL level | | | |
| | Rise/Fall time | Less than 25ns | | | |
| CMOS OUPUT | Output | 4V ~ 15V ± 1V, Continuously Variable | | | |
| | Rise/Fall time | Less than 40ns(at Max, output level) | Less than 110ns(at Max, output level) | | |
| SWEEP | Width | 1:1 to 100:1 | | | |
| | Rate | 20ms to 2s(50Hz to 0.5Hz) | | | |
| | Internal Sweep | Linear | | | |
| | External Sweep | By means of VCF input | | | |
| OUTPUT | Output Voltage | 20Vp-p(Open circuit), 10Vp-p(into 50 Ω) | | | |
| | Attenuator | -20dB | | | |
| | Impedance | 50 Ω ±5% | | | |
| FREQUENCY COUNTER | Display | 6 digit green LED(0.2Hz ~ 50MHz) | | | |
| | Accuracy | ± Timebase Error ± 1count | | | |
| | Input sensitivity | kHz : 100mV, MHz : 300mV | | | |
| | Max. Input voltage | 150Vrm(at 1kHz) | | | |
| GENERAL | Operating Envirnoments | 0°C ~ +40°C, 85% RH | | | |
| | Ranges for Guaranteed | 25°C ±5°C, 70% RH | | | |
| | Power Requirement | AC 115 / 230V ±10°C, 50 / 60Hz | | | |
| | Power Consumption | Approx. 20W | | | |
| | Dimension(mm) | 255(W) × 80(H) × 260(D) | | | 210(W) × 76(H) × 260(D) |
| | Accessories | Power Cord, BNC Cable, Fuse, Operator' s Manual | | | |